



7



Single Shelf Carrier
(top of the bay only)



Double Shelf Carrier



1. Attach plastic feet to the uprights
2. Attach single shelf carrier at the top and a double at the bottom of the frame. Push in lugs with a flathead screwdriver to secure.
3. Attach the remaining double shelf carriers at the desired heights within the bay.
4. Insert the panels into the top and bottom shelf carriers to stabilise the bay.
5. Attach the cross bracing at the back of the bay using the expo spanner + 8mm spanner.
6. Insert the rest of the shelf panels to complete the bay.
7. To add an extension bay, follow steps 1 - 3 with one frame, attach shelf carriers to the outside of the existing bay. Then repeat steps 4 and 6.

Expo 3 Shelf Capacities

Width (mm)	Depth (mm)					
	200	300	400	500	600	800
700	90kg	135kg	180kg	225kg	270kg	300kg
1000	70kg	105kg	140kg	175kg	210kg	280kg
1150	80kg	120kg	160kg	200kg	240kg	300kg
1300	70kg	105kg	140kg	175kg	210kg	280kg

Tools Required

Rubber Mallet, Flat Head Screw Driver
Expo Spanner (included), Spanner 8mm

Safety Precaution

Two competent people wearing safety gloves, safety shoes and protective eyewear are recommended to undertake the assembly.



scan for more info